Blue Max® MIG 308L N

Stainless Steel • AWS ER308/ER308L

Key Features

- Q2 Lot® Certificate showing actual wire composition and calculated ferrite number (FN) available online
- Available as Batch Managed Inventory
- "N" Designator cobalt restriction of 0.05% max
- Meets the low Si levels typically required in the nuclear industry
- Meets the low cobalt levels typically required in the nuclear industry.
- Prior to using this material for ASME Boiler and Pressure Vessel Code Section III applications, please contact the Lincoln Electric Specials Department to receive a Certified Material Test Report (CMTR) which meets all requirements of NCA-3860
- Composition controlled to meet nuclear and power generation requirements
- Each spool is identified with AWS classification and LOT number

Typical Applications

- Nuclear power plant components, maintenance and construction
- Power and process industry related piping
- Pressure Vessels

ASME IX Qualification

ASME IX Qualification: QW432 F-No 6, QW442 A-No 8

Conformances

AWS A5.9/A5.9M: 2006: ER308, ER308L ASME SFA-A5.9: ER308, ER308L

Welding Positions

ΑII

DIAMETERS / PACKAGING

Diameter	33 lb (15 kg)
in (mm)	Steel Spool
0.035 (0.9)	ED033848
0.045 (1.1)	ED033849

MECHANICAL PROPERTIES(1) – As Required per AWS A5.9/A5.9M: 2006

	Yield Strength ⁽²⁾ MPa (ksi)	Tensile Strength MPa (ksi)	Elongation %	Ferrite Number		
Requirements - AWS ER308/308L	Not Specified					
Test Results ⁽³⁾ - As-Welded	430 (62)	615 (89)	37	13		

Blue Max® MIG 308L N (AWS ER308/ER308L)

WIRE COMPOSITION – As Required per AWS A5.9/A5.9M: 2006

	%С	%Cr	%Ni	%Mo	%Mn		
Requirements - AWS ER308L	0.03 ⁽²⁾ max.	19.5 - 22.0	9.0 -11.0	0.75 max.	1.0 - 2.5		
Test Results ⁽¹⁾	0.02	20.2	9.2	0.03	1.6		
	%Si	%P	%S	%Cu	Total Others		
Requirements - AWS ER308L	0.30 - 0.65	0.03 max.	0.03 max.	0.75 max.	0.50 max.		
Test Results ⁽¹⁾	0.44	0.02	0.02	0.11	0.03		

TYPICAL OPERATING PROCEDURES

Diameter, Polarity Shielding Gas	CTWD ⁽⁵⁾ mm (in)	Wire Feed Speed m/min (in/min)	Voltage (Volts)	Approx. Current (Amps)	Deposition Rate kg/hr (lb/hr)		
Short Circuit Transfer							
	13 (1/2)	3.0 (120)	19-20	55	0.9 (2.0)		
	13 (1/2)	4.6 (180)	19-20	85	1.4 (3.0)		
0.035 in (0.9 mm), DC+	13 (1/2)	5.8 (230)	20-21	105	1.8 (3.9)		
90% He / 7-1/2% Ar / 2-1/2% CO ₂	13 (1/2)	7.6 (300)	20-21	125	2.3 (5.0)		
_	13 (1/2)	8.9 (350)	21-22	140	2.7 (5.9)		
	13 (1/2)	10.2 (400)	22-23	160	3.1 (6.7)		
	13 (1/2)	2.5 (100)	19-20	100	1.1 (2.8)		
	13 (1/2)	3.2 (125)	19-20	120	1.5 (3.5)		
	13 (1/2)	3.8 (150)	21	135	1.7 (4.2)		
0.045 in (1.1 mm), DC+	13 (1/2)	4.4 (175)	21	140	2.0 (4.8)		
90% He / 7-1/2% Ar / 2-1/2% CO ₂	13 (1/2)	5.6 (220)	22	170	2.6 (6.1)		
-	13 (1/2)	6.4 (250)	22-23	175	2.9 (6.9)		
	13 (1/2)	7.0 (275)	22-23	185	3.2 (7.6)		
Axial Spray Transfer							
	13 (1/2)	10.2 (400)	22	180	3.1 (6.7)		
0.035 in (0.9 mm), DC+	13 (1/2)	10.8 (425)	23	190	3.3 (7.1)		
98% Ar/2% 0 ₂	13 (1/2)	11.4 (450)	23	200	3.5 (7.5)		
-	13 (1/2)	12.1 (475)	23	210	3.7 (8.0)		
	13 (1/2)	6.1 (240)	23	195	2.8 (6.6)		
	13 (1/2)	6.6 (260)	24	230	3.0 (7.2)		
0.045 in (1.1 mm), DC+	13 (1/2)	7.6 (300)	24	240	3.5 (8.3)		
98% Ar/2% 0 ₂	13 (1/2)	8.3 (325)	25	250	3.8 (9.0)		
<u>-</u>	13 (1/2)	9.1 (360)	25	260	4.2 (10.0)		

IMPORTANT: SPECIAL VENTILATION AND/OR EXHAUST REQUIRED

Fumes from the normal use of some welding products can contain significant quantities of components - such as chromium and manganese - which can lower the 5.0 mg/m³ maximum exposure guideline for general welding fume.

BEFORE USE, READ AND UNDERSTAND THE MATERIAL SAFETY DATA SHEET (MSDS) FOR THIS PRODUCT AND SPECIFIC INFORMATION PRINTED ON THE PRODUCT CONTAINER.

[&]quot;Typical all weld metal. "Measured with 0.2% offset. "See test results disclaimer on pg. 12. "Copper due to any coating on the electrode plus the copper content of the filler metal itself, shall not exceed the stated 0.50% max. "CTWD (Contact Tip to Work Distance). Subtract 1/4 in (6.4 mm) to calculate Electrical Stickout. "Procedures in the shaded areas are procedures for short circuiting mode using 75% Argon, 25% CO₂, NOTE: For 100% CO₂ procedures, add 1 to 2 volts for short circuit transfer and 2 to 3 volts for globular transfer.